# ΜΙΥΟΤΑ

# MOVEMENT SPECIFICATIONS <u>CAL. 6P05/09/25/27/29/89 ANALOG QUARTZ MOV'T</u> BY CITIZEN WATCH CO., LTD. JAPAN <u>MULTI - EYES RANGE</u> MANUFACTURED IN JAPAN

# **1.BASIC SPECIFICATION**

(1) CAL. NO.

CALIBRE	6P05	6P09	6P25	6P27	6P29	6P89			
Ligne Size*mm	10-1/2 22.6 x 22.6 x <i>Φ23.3</i>								
Total height	3.45mm								
Hands	6	7	5	6					
Date	0								
Day of Week	0								
24 hour	Х	0	X		0				
Month	C	)	X			0			
Battery life	3Year								
Battery	SR621SW or equivalent								

### (2) Time standard

Type of quartz : Tuning fork type quartz crystal Frequency : 32,768Hz Accuracy : +/-20 s/month worn under normal circumstances

(3) Battery installed

Type of battery : Silver oxide SR621SW or equivalent

(4) Others

Driving systems : Two-pole stepping motor

(5) Balanceable weight of hand

Minute hand Max. 0.4  $\mu$  N·m Second hand Max. 0.07  $\mu$  N·m

(6) Additional Mechanisms

Calendar	: Date Month Day	(Center, clockwise) (3 o'clock position, clockwise) (9 o'clock position, clockwise)		
Date correction	: Pull out the crown to the first click			
Day correction	: Pull out the crown to the second click			
Month	: Push button			
Picture dial	: Moon phase (Age of the moon dial rotating one turn every 59 days Φ10.1mm) correction by pulling out the crown to the first click (clockwise)			
Power conservation switch	ervation switch : Pull out the crown to the second click			

Second hand stopping devis: Pull out the crown to the second click

## 2. SEPARATED PARTS

CALIBRE	6P05	6P09	6P25	6P27	6P29	6P89		
Setting Stem	065-379							
* Setting stem				065-379				

20.03mm

Φ0.9 x 12.18mm

Length of movement center to stem end... Thread.....

#### 3. Others

#### \* Measurement of time rate

The unit(gate) time of measurement must be set at "10s " or integer fold value of 10s owing to the DFC system, and the measurement must be performed in the form of complete watch.

#### \* Marking on movement

## MIYOTA CO. UNADJUSTED NO JEWEL JAPAN 6P50

#### \* Typical clearance

 Mov't - Caseback
 minimum 150 μm or more

 Top of hands - Glass
 300 - 400 μm \*

 \* depending and subject to the glass and case structure, and hand length

#### 4. Notice Of Casing

- (1) The month corrector button should be hidden for preventing the error of action.
- (2) The returning pressure of the month corrector button should be Min.200g
- (3) The interval between Dial and Glass end should be 150  $\mu$  m to avoid breakage under drop.

#### **5.Setting Instructions**

(1) setting the day

Set the day by pulling out the crown to second click position and rotating it forward ( to rotate the hour and minute hands clockwise).

If the day is set by rotating the crown backyard (rotating the hour and minute hands counter-clockwise), the date may not be changed.

Note: The day is changed during the period from about 0:00 AM to about 5:30 AM

(2) Setting the date (Quick change function)

Pull the crown out to the first click position and set the date by rotating the crown backyard.

If the date is set beween 9:00 PM and 0:00 AM, the date will not change correctly.

(3) Setting the normal time

Pull the crown out to the second click position when the second hand reaches the 12 o'clock position so that the second hand stops there.

Then set the hour and minute hands.

When setting the minute hand, put it 4 to 5 minutes earlier than the time to be set, and then turn it back to the correct time.

Note: The day is changed during the period from about 0:00 AM to about 5:30 AM. After the time is set, push the crown back simultaneously with the time signal. The second hand will start running at the same time.

(4) Setting the month

Each time the month setting button is pushed, the month is moved clockwise by one month. If the button is not pushed to the end, the month is not changed perfectly. Be sure to push it to the end firmly.

The month changes at about 0:00 AM on the 1st day of the next month.

Note: Do not change the month while the date hand lies between the 26th and the 31st. In this case, set the date hand out of this period to adjust the month after this operation, set the date hand again.

When the time passes from a month with 30 or less days to a 31-day month, please correct the date hand. The month is also changed automatically.

This specifications might be changed without prior notice.







